1-E3561-301

OMD Mk6 detector

Product overview

The Mk6 detectors use optical sensing; (light scatter) as it's detection method and continually monitors the oil mist density in the crank space to which it is connected. In addition, the detector automatically performs self-checks for any internal faults. The control panel interrogates each detector in turn, identifying each detector by a unique address, to obtain the oil mist density value and determine the status of the detector.

Each detector is fitted with 3 LED indicator lights:
- Green: Power on
- Red: Alarm
- Amber: Fault

As all detectors operate independently, the loss of one detector through a fault does not affect the operation of the remaining system. Individual detectors, or engine groups, can be isolated from the system for maintenance while the rest of the system remains in operation.

The Graviner Mk6 Oil Mist Detection system supports up to 64 detectors.



Details

- Engine mounted
- Suitable for both 2 stroke and 4 stroke engines
- Uses optical sensing (light scatter)
- Intelligent stand-alone device
- Measures oil mist density and transmits level to the control panel
- Continuous fault and oil contamination monitoring
- Each detector monitors a single crank space
- Eliminates need for external engine pipework
- No requirement for a compressed air supply

1-E3561-301
OMD Mk6 detector

Technical specifications

General

Status indication	Green: power on, Red: alarm, Amber: fault LED’s

Electrical

Power consumption	2.8 W

Detection

Detection principle	Light scatter
Sensitivity	0.1 to 2.6 mg/l
Particle sensitivity range	0.1 to 5 µm

Sampling pipe

Length	83 mm

Physical

Colour	Black

Environmental

Operating temperature	0 to +70°C
Storage temperature	-20 to +60°C
IP rating	IP65

As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 21 August 2026 - 14:33