


TruVision TVMI-PM Multi-imager Pendant Mount Bracket Installation Instructions

Description

Figure 1: Physical description

Dimensions: 116.5 × 57 mm (4.59 × 2.24 in.)



Weight: 380 g (0.84 lb.)

Supported camera: TVS-5101

Screws Bolts M8×30 mm (5 pcs)



Screws PM4×12 mm (2 pcs)
(pre-installed on the mount)




Installation

To attach the multi-imager camera to the pendent mount bracket:

1. Choose the appropriate location on the mounting surface. Use the pendant base

to mark the holes for the mounting hardware.

2. Drill holes in the mounting surface and install the four expansion anchors.




Note: Depending on the type of ceiling, you may need to use other screws (not included) to install the pendant mount bracket.

3. Provide an access pole in the mounting surface for the camera interface cables.
4. Route the cables through the pendant mount base and tube.
5. Secure the pendant mount base to the mounting surface using the hardware provided.
6. Install the cup base on to the pendant mount by lining up the insert with the flat section of the cup base collar. Rotate the cup base 90 degrees. Tighten with the 2 hex head locking screws using the hex wrench that is provided with the multi-imager camera. Clip the safety lanyard that is attached to the cup base to the pendant mount.

Locking screw



7. Route the camera interconnect cables through the multi-imager camera. If you are not using all the features/cables, you may want to tuck them behind the adapter plate to keep them out of the way so they do not interfere when installing the camera on the pendant mount.
8. Tighten the Phillips head set screw on the pendant mount.
9. To complete camera installation, refer to the installation instructions for the specific cup base and camera.



Contact information

EMEA: <https://firesecurityproducts.com>

Australia/New Zealand:

<https://firesecurityproducts.com.au/>

Product documentation

Please consult the following web link to retrieve the electronic version of the product documentation. The manuals are available in several languages.



Legal information

Copyright

© 2026 Kidde Global Solutions.
All rights reserved.
Specifications subject to change
without prior notice.

Trademarks and patents

TruVision names and logos are
a product brand of Aritech

Certification

